

MGS-2 Mini-Ganzfeld System

USER'S MANUAL

Version 1.1

LKC Technologies, Inc.
2 Professional Drive, Suite 222
Gaithersburg, MD 20879 USA
(301) 840-1992
(800) 638-7055
lkc@his.com

WARRANTY

LKC Technologies, Inc. unconditionally warrants this instrument to be free from defects in materials and workmanship, provided there is no evidence of abuse or attempted repairs without authorization from LKC Technologies, Inc. This Warranty is binding for one year from date of initial delivery and is limited to: servicing and/or replacing any instrument, or part thereof, returned to the factory for that purpose with transportation charges prepaid and which are found to be defective. This Warranty is made expressly in lieu of all other liabilities and obligations on the part of LKC Technologies, Inc.

DAMAGE UPON ARRIVAL. Each instrument leaves our plant, after rigorous tests, in perfect operating condition. The instrument may receive rough handling and damage in transit. The shipment is insured against such damage. The Buyer must report, in writing, immediately any concealed or apparent damage to the last carrier. Report any damage also to us, and issue an order for replacement or repair.

DEFECTS OCCURRING WITHIN WARRANTY PERIOD. Parts of units may develop defects which no amount of initial testing will reveal. The price of our instruments makes provision for such service, but it does not:

1. Provide for transportation charges to our factory for service,
2. Provide for services not performed or authorized by us,
3. Provide for the cost of repairing instruments that have obviously been abused or subjected to unusual environments for which they have not been designed.

We will be happy at any time to discuss by phone, letter, FAX, or e-mail suspected defects or aspects of instrument operation that may be unclear. We advise you to inform us by phone, letter FAX, or e-mail of the nature of the defect before returning an instrument for repair. Often, a simple suggestion will solve the problem without returning an instrument to the factory. If we are unable to suggest something that solves the problem, we will advise you as to what parts of the equipment should be returned to the factory for service.

DEFECTS OCCURRING AFTER WARRANTY PERIOD. Charges for repairs after the warranty period will be based upon actual hours spent on the repair at the then prevailing rate, plus cost of parts required and transportation charges, or you may elect to purchase an extended warranty.

We will be happy to discuss by phone, letter, FAX, or e-mail any problem you may be experiencing.

LKC Technologies, Inc.

Customer Support
(800) 638-7055

FAX Number
(301) 330-2237

e-mail
lkc@his.com

Introduction

The MGS-2 is a stand-alone monocular ganzfeld photic stimulator designed for use in visual electrodiagnostic testing. The stimulator conforms to the requirements of the ISCEV *Standard for Clinical Electretinography*. The MGS-2 is designed to be used with your existing electrophysiology recording system to perform the electroretinogram (ERG) or flash visually evoked potential (flash VEP).

The equipment has been tested in accordance with AAMI Safe Current Limits Standard and meets all requirements for Non-isolated Patient Connections, i.e., electromedical apparatus with intentional electrical or conductive contact, other than contacts intended to be connected to the exposed heart or to a foreign conductive pathway to the heart or great vessels.

This equipment is offered for sale only to qualified Health Professionals.

Setting up the MGS-2

Before you can use the MGS-2, you must set it up, connect it to your recording system, and configure it to match your recording system.

The MGS-2 system consists of two parts:

- The Main Unit (the box)
- The Hand held Mini-Ganzfeld Stimulator (called the Kürbisfeld)

Step 1

Make sure the MGS-2 is properly configured to match your recording system. See the section titled *Configuring the MGS-2 to Match Your System* on the next page. If you have trouble figuring this out, call or send a fax/e-mail to the customer support at LKC for assistance.

Step 2

Plug the Kürbisfeld into the Main Unit.

- ☛ **Make sure the power to the Main Unit is off before connecting or disconnecting the Kürbisfeld.**

Step 3

Plug the Main Unit into the power mains. If you are using the MGS-2 with an LKC EPIC-1000 or UTAS-E 2000 system, plug the unit into one of the outlets on the back of the Interface Unit. If you are using the MGS-2 with an LKC EPIC-2000 system or with a system from another manufacturer, you may plug the MGS-2 directly into a wall outlet.

- ☛ **The MGS-2 uses an “Universal” power supply. As such, it can be connected to any AC power source from 100 Volts to 220 Volts at either 50 or 60 Hz.**

Step 4

Connect the MGS-2 to your recording system using the cable provided with the unit. See the instructions in *Configuring the MGS-2 to Match Your System* on the next page to determine how to connect the cable.

- ☛ **You are now ready to use your MGS-2 stimulator.**

Configuring the MGS-2 to Match Your System

To function properly as a stimulator, the MGS-2 must communicate with your recording system. The MGS-2 can do this in one of two ways:

- The MGS-2 can accept a trigger signal from your recording equipment and trigger its stimulus by this signal.
 - The MGS-2 can provide a trigger signal to your system to inform it that the stimulus has been triggered, by pressing the **STIM** button either on the Main Unit or on the stimulator.
- ☛ **The first step in configuring the MGS-2 is to decide whether the recording system or the MGS-2 will trigger the stimulus.**

If the MGS-2 is to accept a trigger signal from your recording system:

- Connect a cable from the trigger output of your recording system to the connector marked **TRIGGER IN** on the rear of the MGS-2.

You must also make sure that the MGS-2 is set to properly trigger from your recording system. The MGS-2 accepts a TTL-level (0 to 5 V) trigger input signal. As it comes from the factory, the MGS-2 will fire stimulus each time the trigger input signal, applied to **TRIGGER IN**, goes from **low** (0 V) to **high** (5 V). Consult the manual for your recording system or measure its trigger signal with an oscilloscope to determine its polarity.

Warning: If the Trigger In Polarity Switch is improperly set, the MGS-2 may appear to operate correctly, but the timing of the stimulus will be incorrect.

If the trigger signal from your system goes from **high** (5 V) to **low** (0 V), set the trigger-in-polarity switch SW9-3 on PCB 310134 to the **on** position.

If the MGS-2 is to provide a trigger signal to your recording system:


- Connect a cable from the connector marked **TRIGGER OUT** on the rear of the MGS-2 to the external trigger input of your recording system.

You must also make sure that the MGS-2 is set to send the proper trigger to your recording system. As it comes from the factory, the MGS-2 sends a TTL-level trigger signal to **TRIGGER OUT** that goes from **low** (0 V) to **high** (5 V) to the recording system each time a stimulus occurs. Consult the manual for your system to determine if this is the correct polarity.

Warning: If the Trigger Out Polarity Switch is improperly set, the MGS-2 may appear to operate correctly, but the timing of the stimulus will be incorrect.

If your system requires a trigger signal going from **high** (5 V) to **low** (0 V), set the trigger-out-polarity switch SW9-2 on PCB 310134 to the **on** position.

Setting the MGS-2 switches.



Remove the four screws on the bottom of the MGS-2 box and lift off the top cover.

The rocker DIP switch SW9 is located on the circuit board PCB 310134 mounted to the back of the front panel. You will need to slide the front panel out of the bottom cover to gain access to the switch. Turn on or turn off switches of SW9 according to the following tables.

SW9-1, Trigger Out Select Switch	
ON <input type="checkbox"/>	TTL - level trigger output signal
OFF	Open - Collector trigger output signal


SW9-2, Trigger Out Polarity Switch	
ON	Trigger output goes high to low at stimulus
OFF <input type="checkbox"/>	Trigger output goes low to high at stimulus

SW9-3, Trigger In Polarity Switch	
ON	Stimulus triggers on high to low transition
OFF <input type="checkbox"/>	Stimulus triggers on low to high transition

System default settings.

Using the MGS-2

After you have properly set up your MGS-2, you are ready to start using it.



Turning it On and Off

The power switch for the MGS-2 is located on the rear of the unit. It is the only switch on the Main Unit that is not labeled. When you turn the MGS-2 on, the LCD display window on the Main Unit will glow with green light and show the information as above, and the 7 push buttons will turn red. Whether the fixation light in the Kürbisfeld glows a dim red or remains off depends on the last setting before the system was previously powered off.

After 3 seconds, the LCD display will turn to the **Main Menu**.

Main Menu

The **Main Menu** displays function names (also sub-menu names) and the current settings of flash/flicker intensity and back light brightness:

Main Menu
→ **Flash** **Background**
 Flicker
B: 30 cd/m² **F: 0 dB**

MGS-2 can save all the settings in its memory. Each time when the system is powered on, the **Main Menu** will show the last settings before it was powered off. The first time you power your MGS-2 the default settings of the system should be shown as above, which means:

Stimulus Type: Flash
Background Light: 30cd/m²
Flash/Flicker: 0dB (2.5cd·s/m²)

Pressing the **BACK LIGHT** button on the front panel or the **BKLT** button on the back of the Kürbisfeld will turn on the background light.

The brightness of background light is 30 cd/m². The status of fixation light, ON or OFF can be selected in the **Background** sub-menu.

Pressing the **STIM** button either on the front panel or on the back of the Kürbisfeld will trigger the stimulus. At the same time, the system will send a trigger output pulse to the **TRIGGER OUT** BNC connector on the rear panel.

☞ **The [STIM] and [BACK LIGHT] buttons are operational only when the Main Menu is displayed.**

MGS-2 provides 2 kinds of stimuli: Flash and Flicker. The features of each stimulus can be set in the according sub-menu. Flash/flicker of any available intensity can be triggered individually or with background light.

When the **STIM** button is pressed, it will

- fire a single flash if the cursor arrow points to **Flash** or **Background**.
- start flicker until the **STIM** button is released if the arrow points to **Flicker**.

☞ **If the MGS-2 is set to accept a trigger signal from your recording system, make sure that external trigger input signals can be accepted by the MGS-2 only at the Main Menu.**

Each trigger input pulse fires a single flash no matter the cursor arrow is pointing to **Flash, Flicker** or **Background**. Flicker can be obtained by sending periodical pulses to the unit at any rate less than 100Hz.

Use buttons **▲ ▼ ←** and **→** to select functions/sub-menus. Press the **SEL** button to switch to the according sub-menu. Features for any function, e.g., intensity, rate, etc. can be re-selected in the sub-menus.

Flash Menu

Flash

Intensity: * 0dB

The value beside the * symbols is the current flash level. Using buttons **←** or **→** can make a change. Once button **←** or **→** is pressed, the symbol * will turn to a pointer **➡**, which indicates that no option is selected yet. Press the **SEL** button to select the dB value. After a value is selected, shown by the pointer turning back to the star, press **SEL** again to return to the **Main Menu**.

Available flash intensities are: -25 through +5 dB in 5dB steps.
(0 dB: 2.5 cd·s/m²)

Flicker Menu

Flicker

Intensity: * 0dB
Flicker Rate: * 30Hz

The Intensity/Flicker Rate features with * symbols are the current settings. Use buttons ▲ and ▼ to point to one of the two features. Press button ← or → to make a change to the feature. Once button ← or → is pressed, the symbol * will turn to a pointer ➡, which indicates that no option for the feature is selected yet. Press the **SEL** button to select an option. After both two features are selected, press **SEL** again to return to the **Main Menu**.

Flicker Intensity: -25 through +5 dB in 5dB steps.
Flicker Rate: 5Hz through 60Hz in 5Hz steps.

Background Menu

Background

Intensity: *30 cd/m²
Fixation: *ON OFF

Background intensity is 30cd/m². The current fixation status is indicated by the * symbol. Pressing button ← or → can toggle between ON and OFF. Once button ← or → is pressed, the symbol * will turn to a pointer ➡, which indicates that no option for the feature is selected yet. Press the **SEL** button to select the option then press **SEL** again to return to the **Main Menu**.

Computer Control

MGS-2 is also computer-controllable using a RS-232 serial port. If you need to use this feature, please contact LKC for further information.

Presenting Stimuli to the Patient

To present a stimulus to the patient, hold the Kürbisfeld up to the patient's eye.

- The ERG requires a ganzfeld stimulus, and the Kürbisfeld must be close to the patient's eye to assure that light enters the eye evenly from all directions. Be careful that the Kürbisfeld does not dislodge the corneal electrode when it is placed over the eye.
- Flash VEP does not require a ganzfeld stimulus, and the Kürbisfeld may be held 10 to 15 cm (4 to 6 inches) from the patient's eye.

 **Press the STIM button on the Kürbisfeld to present a stimulus to the patient.**

If the Main Unit is set to **Flash**, a single flash of the selected intensity will be presented. If the Main Unit is set to **Flicker**, a flickering stimulus will be presented until the **STIM** button is released.¹

¹ The Main Unit will send a pulse to the Trigger Out connector for each flash during this period.